



# SPECIFICATIONS FOR MODEL GPP FULL SERVICE REDUCED VOLTAGE PART WINDING STARTER ELECTRIC FIRE PUMP CONTROLLER

## LISTING AND APPROVAL

The electric fire pump controller shall meet the latest NFPA 20 requirements, be listed with UL (in accordance with UL218 and CSA C22.2 No. 14 Industrial Control Equipment), approved by FM Global (in accordance with approvals Class 1321/1323) and by the City of New York for fire pump service.

## STARTING METHOD

The electric fire pump controller shall be a full service combined manual and automatic type suitable for reduced voltage part winding starting of the electric fire pump motor.

## SHORT CIRCUIT WITHSTAND RATING

The short circuit withstand rating of the electric fire pump controller shall be 100 kA RMS at 200V - 480V or 50 kA RMS at 600V.

## ENCLOSURE

The standard enclosure shall be NEMA type 2 (IP31). The enclosure shall incorporate a bottom entry gland plate for power and or motor lead entrance. The gland plate shall be field removable and meet the same NEMA rating of the enclosure. Lifting lugs shall be provided.

## POWER CIRCUIT COMPONENTS

The electric fire pump controller shall be supplied with the following power components:

- Voltage surge arrestor
- Motor rated combination isolating switch and circuit breaker assembly. Both the isolating switch and circuit breaker shall be rated not less than 115% of the motor full load current.
- The circuit breaker overcurrent sensing shall be non-thermal type, magnetic only.
- Locked rotor protector set to automatically trip the circuit breaker within 8 to 20 seconds at 600% of full load current. The locked rotor protector shall be factory calibrated, set and tested.
- A part winding electric motor starter

## OPERATIONAL COMPONENTS

The electric fire pump controller shall be supplied with the following externally flange mounted components approved to match the NEMA rating of the enclosure:

- One common operating handle for both the isolating switch and the circuit breaker assembly mechanically interlocked with the enclosure door to prohibit access to the interior in the "ON" position.
- One "Emergency Start" and run handle mechanism latchable in the "ON" position

## TOUCH SCREEN OPERATOR INTERFACE

The electric fire pump controller shall be supplied with a 4.2" LCD color touch screen (HMI

technology) operator interface powered by an embedded microcomputer with software PLC logic. The operator interface's touch screen shall allow navigation through the various operating screens.

The following keypad type pushbuttons shall be provided:

- Start
- Stop
- Run test
- Navigation
- Help
- Home
- Alarms
- Settings/Configuration
- History/Statistics

The touch screen operator interface shall graphically display:

- Voltage and amperage readings of all three phases simultaneously and independently displayed with true RMS technology.
- Motor starting transition
- Motor stopped / running
- Type of starting cause
- Actuation mode
- Type of controller
- Method of shutdown
- Time and date
- Pump room temperature (°F or °C)
- System pressure in 5 different user selectable units of measure;
  - PSI
  - kPA
  - Bar
  - Feet of head
  - Meter of water

The touch screen operator interface shall allow for the programming and display of:

- Cut-In and Cut-Out pressure settings
- Minimum run period timer
- Sequential start timer
- Periodic test timer

The user shall be able to select the language of operation on-site.

Contextual HELP screens shall be accessible to the user while navigating through the operator interface in the chosen language.

## CONDITION AND ALARM VISUAL INDICATORS

The touch screen operator interface shall visually indicate the following alarms and differentiate the criticalness by color code:

- Normal power phase reversal
- Normal power phase loss
- Normal power loss
- Locked rotor
- Fail to start
- Service required



# SPECIFICATIONS FOR MODEL GPP FULL SERVICE REDUCED VOLTAGE PART WINDING STARTER ELECTRIC FIRE PUMP CONTROLLER

- Undercurrent
- Overcurrent
- Under voltage
- Overvoltage
- Phase unbalance
- Low water level
- Low system (discharge) pressure
- Periodic test cut-in not reached
- Run test solenoid valve check
- Faulty pressure transducer
- Pump on demand
- Over pressure
- Under pressure
- Low pump room temperature

## PRESSURE AND EVENT RECORDING

The fire pump controller's touch screen operator interface shall be capable of logging pressure data and operational events with time and date stamp. It shall be able to display the last 500 operational events and display the pressure data in text and/or graphic form. Under regular maintained operation, pressure data and operational events can be stored in memory for up to five years. The data shall also be retrievable and downloadable to a flash memory disk via the USB port accessible to the user without having to open the controller door. General system information, events and alarms include the following:

- Last service statistics
  - Powered since
  - On time
  - Motor last run
  - Motor run time
  - Motor start count
  - Minimum, maximum, average system pressure
  - Minimum, maximum, average pump room temperature
- All time statistics
  - First power up
  - First start up
  - On time
- Power statistics
  - Voltage between phases with date stamp
  - Amperage between phases with date stamp

## WETTED PARTS

The electric fire pump controller shall be supplied with a pressure transducer and run test solenoid valve assembly. The pressure sensing line connection to the pressure transducer shall be ½" FNPT. Provision for a redundant pressure transducer shall be provided. This assembly shall be rated for 500psi working pressure (calibrated at 0-300psi) and be externally mounted with a protective cover.

## SERVICE/FLOW TESTING CAPABILITIES

The electric fire pump controller's touch screen operator interface shall have the capability of scheduling maintenance reminders. It shall also have the capability of inputting pump flow test data, generate and display the pump curve and store this information in memory for the lifetime of the controller.

## CONNECTION FOR EXTERNAL DEVICES

The electric fire pump controller shall provide terminals for the connection for the following external devices:

- Manual remote start device
- Automatic remote start device
- Deluge valve start

## ALARM CONTACTS FOR REMOTE INDICATION

SPDT dry alarm contacts rated for 8A – 250VAC for remote indication shall be provided for the following conditions;

- Power or phase failure and/or circuit breaker in open position
- Phase reversal
- Pump run (X2)
- Common pump room alarm (field re-assignable)
- Common motor trouble (field re-assignable)
- Field programmable

Removable alarm contact terminals shall be provided.

## AUDIBLE ALARM

A 4" alarm bell rated for 85dB at 10ft (3m) shall sound during boot up and internal communication error.

## MANUFACTURER

The electric fire pump controller shall be a Model GPP with ViZi Touch operator interface as manufactured by Tornatech Inc.